



### PRODUCT FEATURES

- Backup device in case of exit sensor failure per BOCA, NFPA, IBC, and VBC code
- SPST 3A wet N/C contacts
- Momentarily pressing the EEB releases the door for 30-seconds
- Re-triggerable for added 30-second release
- Field-selectable 12 VDC or 24 VDC to match lock voltage
- Interchangeable green and red lenses included standard
- MagnaCare® lifetime replacement, no fault warranty

### PRODUCT OPTIONS

- Single gang
- Narrow stile
- EEB2 includes standard lenses plus blue ADA lens
- Illumination kits

### SPECIFICATIONS

- (EEB2, EEB3N only)
- ANSI/UL 294 Listed
  - CSA-C22.2 No.205 Listed
  - CSFM – California State Fire Marshal

# EEB

## Emergency Exit Button

### Redundant Backup Ensures Safe Egress

Install the EEB Emergency Exit Button next to the door to provide additional safety and redundancy as required by code when using a motion detector for a request-to-exit device.

### » MODELS

PART #	Description
EEB2	EEB w/ 30 Sec. Timer - Single Gang, SPST, Grn/Red/Handicap
EEB3N	EEB w/ 30 Sec. Timer - Narrow Stile, SPST, Grn/Red
PB2-LK	Illumination Kit for PB2E, PB5E, EEB2 Series Push Buttons
PB3-LK	Illumination Kit, Grn/Red for PB3E/EEB3N Series



**Note:** Securitron's UL294 certification indicates that when the EEB is used with the XMS Motion Sensor, it meets the NFPA Life Safety Code 101 requirements for exit of access-controlled egress doors.



DUAL VOLTAGE



SMART  
MAGNALOCKS  
DURABLE  
MAGNALOCKS  
SPECIALTY  
LOCKS  
EXIT  
DEVICES  
ENTRY  
DEVICES  
ACCESS CONTROL  
ACCESSORIES  
POWER  
SUPPLIES  
POWER  
TRANSFER  
POWER  
ACCESSORIES  
RESOURCES